

INTRUDER ALARM SYSTEM

The **PD-37i** series panels are NEXT Level of Intruder alarm control panel. **PD-37i** have many features of PD-18i and also have New features which makes PD-37i a leader in the segment. Best suitable for Banks, Multi-Branch organizations and other financial institutes.

- 32 wireless Zone & 8 Wired Zone. Expandable to 128 Zones
- Inbuilt PSTN dialer, GSM & IP Module
- CMS Client (Windows) & Android Mobile App for easy use and real time monitoring
- 4 Partition which can be armed, disarmed independently.
- 8 Wired Keypad, 4 Wireless Keypad can be added for system access & operation.
- Event based Programmable Alert Type (SMS, E-mail, Phone Call, CMS)
- Remote Programming via Android App, Web, CMS Client
- Remote Arming / Disarming via Android App, Web, CMS Client, Phone call
- 2 time set for arming & dis-arming the systems
- 800 Event Log for everything happened for in the Panel, can be accessed by Web, App, CMS
- 32 user, 1 Master and 1 Admin password support
- Complete Health monitoring of the system
- Individual Wireless Detector Low Battery, Tamper, Loss alerts via Log, SMS, CMS
- Support wide range of wireless sensors : PIR, Door/Window sensor, Panic Switch, Vibration, Shutter sensor, Glass Break Sensor, Key-fob, SOS, Smoke sensors
- Support 4 Wireless Sounder
- Support universal wired sensors with Normally Open, Normally Close & EOL wiring pattern
- Dual Antenna for long range reception of signals
- 4 PMW (Programmable Output) for various Events / Alerts
- Internal space to install Maintenance free Battery (12v-7AH) with over charging & deep discharge protection
- Tamper alarm if panel removed from location or opened
- Elegant & Sleek white color design
- Certified by ERTL (N) & CE

PD-37i

